

KUBOTA

GENERATING SET POWER SELECTOR



Kubota

Specifications 50Hz 400-230V

General Specification

| GENTSETS | KVA/KW Cos 0.8 | | Engine Type | Max Output KW | CYL | Bore | Stroke | DSPL | Fuel Cons 100% | GOV. |
|----------|------------------|----------------|-------------|------------------|-----|------|--------|------|-------------------|------|
| | Standby Power | Prime Power | | | | | | | | |

| | | | | | | | | | | |
|---------|-------|-------|---------|--|----|--|--|--|-------|------------|
| M-KBT8 | 8/7 | 8/6 | D1105 | | 3L | | | | 2.93 | Mechanical |
| M-KBT11 | 11/9 | 10/8 | V1505 | | 4L | | | | 3.89 | Mechanical |
| M-KBT14 | 14/11 | 13/10 | D1703 | | 3L | | | | 4.14 | Mechanical |
| M-KBT20 | 19/15 | 18/14 | V2203 | | 4L | | | | 5.54 | Mechanical |
| M-KBT22 | 22/18 | 20/16 | V2003-T | | 4L | | | | 6.72 | Mechanical |
| M-KBT27 | 28/22 | 25/20 | V3300 | | 4L | | | | 9.18 | Mechanical |
| M-KBT33 | 33/26 | 30/24 | V3300-T | | 4L | | | | 10.88 | Mechanical |